# **Data Sheet**

# **EMP Protector** 3402.17.K

# **IUBER+SUHN**

### **Description**

GDT technology up to 2.5 GHz

#### **Benefits**

Broad-band design

DC continuity for remote powering


GDT holder with chain

The protector can also be installed reversely

Delivered without gas discharge tube

Data refer to GDT 9071.99.0547, 230 V

Compliant to IEC 61643-21



## **Product Configuration**

Main path connectors Mounting and grounding Side of bulkhead

Port 1: unprotected, N jack (female) - Port 2: protected, N jack (female)

MH25 (bulkhead mounting), brk (bracket)

protected side

#### **Technical Data**

#### **Electrical Data**

Impedance 50 Ω

0 - 2500 MHz 0 - 1000 MHz Frequency range Return loss ≥ 20 dB ≥ 26 dB ≤ 0.2 dB ≤ 0.1 dB Insertion loss ≤ 150 W RF CW power ≤ 150 W PIM 3rd order not specified not specified

Surge current handling capability

30 single / 20 multiple kA (test pulse 8/20 µs) Residual pulse energy

350  $\mu J$  typically (test pulse 4 kV 1.2/50  $\mu s$  / 2 kA 8/20  $\mu s$ ) main path - protected side

**Mechanical Data** 

Number of matings 500 150 g Weight

**Environmental Data** 

Operating temperature -40 °C to +85 °C

Waterproof degree IP66 (according to IEC 60529, data refer to the coupled state)

2011/65/EC (RoHS) compliant

#### **Material Data**

Piece Parts	Material	Surface Plating
Housing	Brass	SUCOPLATE (R) Plating
Port 1 center contact	Copper Beryllium Alloy	Gold Plating (without Nickel underplating)
Port 2 center contact	Copper Beryllium Alloy	Gold Plating (without Nickel underplating)

## **Related Documents**

Outline drawing DOU-00004083.1 Mounting instruction DOC-0000176104

#### Remarks

Customer part number NATO: NSN 5920-12-332-5482

HUBER+SUHNER is certified according to ISO 9001, ISO 14001, AS/EN9100, ISO/TS 16949 and IRIS.

www.hubersuhner.com

Waiver: Fact and figures herein are for information only and do not represent any warranty of any kind.

Document: DOC-0000177042 AA / PDO N / date of publication: 28.02.2019 17:17:04 / uncontrolled copy